


Maximum loading of automatic circuit breakers



Alice

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96666073	ALICE LED FL IP65 10W 840	113	149	182	233	115	150	185	235
96628836	ALICE LED FL IP65 20W 840	53	72	90	113	55	75	93	115
96666074	ALICE LED FL IP65 30W 840	62	85	108	132	65	89	110	135
96666075	ALICE LED FL IP65 50W 840	38	52	63	80	40	54	65	82
96666076	ALICE LED FL IP65 100W 840	18	25	30	40	20	27	33	41



Amy

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96665583	AMY 100 LED DL 800 830	176	229	282	352	106	138	170	212
96665584	AMY 100 LED DL 800 840	176	229	282	352	106	138	170	212
96628352	AMY 150 LED DL 1000 830	132	172	211	264	80	103	127	159
96628353	AMY 150 LED DL 1000 840	132	172	211	264	80	103	127	159
96665585	AMY 150 LED DL 1500 830	99	129	158	198	60	78	95	119
96665586	AMY 150 LED DL 1500 840	99	129	158	198	60	78	95	119
96665587	AMY 200 LED DL 2000 830	75	98	120	150	45	59	72	90
96665588	AMY 200 LED DL 2000 840	75	98	120	150	45	59	72	90
96665848	AMY 150 LED DL 1000 830 E3	132	172	211	264	80	103	127	159
96665849	AMY 150 LED DL 1000 840 E3	132	172	211	264	80	103	127	159
96665844	AMY 150 LED DL 1500 830 E3	99	129	158	198	60	78	95	119
96665845	AMY 150 LED DL 1500 840 E3	99	129	158	198	60	78	95	119
96665846	AMY 200 LED DL 2000 830 E3	75	98	120	150	45	59	72	90
96665847	AMY 200 LED DL 2000 840 E3	75	98	120	150	45	59	72	90




Anna

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96630066	ANNA LED Q596 3500 840	47	60	75	95	26	35	43	55
96630068	ANNA LED Q596 3500 840 E3	47	60	75	95	26	35	43	55
96630069	ANNA LED Q596 3200 830	47	60	75	95	26	35	43	55
96630359	ANNA LED Q596 3500 840 TpA	47	60	75	95	26	35	43	55
96630360	ANNA LED Q596 3500 840 TpA E3	47	60	75	95	26	35	43	55
96631113	ANNA LED Q596 3500 840 HFIX	21	30	36	46	13	18	22	28
96631115	ANNA LED Q596 3500 840 HFIX E3	21	30	36	46	13	18	22	28
96631116	ANNA LED Q596 3200 830 HFIX	21	30	36	46	13	18	22	28
96631118	ANNA LED Q596 3500 840 HFIX TpA	21	30	36	46	13	18	22	28
96631119	ANNA LED Q596 3500 840 HFIX TpA E3	21	30	36	46	13	18	22	28



Elsa

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96630327	ELSA LED 600 1200 840 WH	80	100	125	160	80	100	125	160
96630328	ELSA LED 600 1200 830 WH	80	100	125	160	80	100	125	160
96630329	ELSA LED 600 1200 840 MWS WH	80	100	125	160	80	100	125	160
96630330	ELSA LED 600 1200 830 MWS WH	80	100	125	160	80	100	125	160
96630376	ELSA LED 450 800 840 WH	80	100	125	160	80	100	125	160
96630377	ELSA LED 450 800 830 WH	80	100	125	160	80	100	125	160
96630378	ELSA LED 450 800 840 MWS WH	80	100	125	160	80	100	125	160
96630379	ELSA LED 450 800 830 MWS WH	80	100	125	160	80	100	125	160



Fred

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96630340	FRED LED IP65 75 550 840	166	216	266	333	150	200	250	320
96630341	FRED LED IP65 75 550 830	166	216	266	333	150	200	250	320



George

SAP Code	Product Description	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25
96630323	GEORGE LED 330 12000 840	17	22	22	34	43	8	8	13	17	21
96630324	GEORGE LED 330 18000 840	5	6	6	10	12	2	2	4	5	6
96630325	GEORGE LED 390 24000 840	5	6	6	10	12	2	2	4	5	6
96630326	GEORGE LED 390 30000 840	3	4	4	7	9	1	1	3	3	4



Julie

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96628557	JULIE 600 LED IP65 1200 840	47	61	76	9	47	61	76	9
96628548	JULIE 600 LED IP65 1800 840	22	28	35	44	22	28	35	44
96631255	JULIE 1200 LED IP65 3000 840	18	24	29	37	18	24	29	37
96631404	JULIE 1200 LED IP65 3000 840 E3	15	19	24	30	15	19	24	30
96665578	JULIE 1200 LED IP65 4000 840 CONNECT	12	16	20	29	20	27	33	40
96665577	JULIE 1200 LED IP65 4000 840	12	16	20	29	20	27	33	40
96665579	JULIE 1200 LED IP65 4000 840 E3	12	16	20	29	20	27	33	40
96630234	JULIE 1200 LED IP65 4000 840 COR MWS	12	16	20	29	20	27	33	40
96630237	JULIE 1200 LED IP65 4000 840 COR MWS CON	12	16	20	29	20	27	33	40
96630239	JULIE 1200 LED IP65 4000 840 TW	12	16	20	29	20	27	33	40
96631093	JULIE 1200 LED IP65 4000 840 COR MWS E3	12	16	20	29	20	27	33	40
96628396	JULIE 1500 LED IP65 4000 840	12	16	20	29	20	27	33	40
96628397	JULIE 1500 LED IP65 4000 840 E3	12	16	20	29	20	27	33	40
96630235	JULIE 1500 LED IP65 4000 840 COR MWS	12	16	20	29	20	27	33	40
96631094	JULIE 1500 LED IP65 4000 840 COR MWS E3	12	16	20	29	20	27	33	40
96630240	JULIE 1500 LED IP65 4000 840 TW	12	16	20	29	20	27	33	40
96665580	JULIE 1500 LED IP65 6000 840	11	14	17	27	18	25	31	38
96665581	JULIE 1500 LED IP65 6000 840 CONNECT	11	14	17	27	18	25	31	38
96665582	JULIE 1500 LED IP65 6000 840 E3	11	14	17	27	18	25	31	38
96630236	JULIE 1500 LED IP65 6000 840 COR MWS	11	14	17	27	18	25	31	38
96630238	JULIE 1500 LED IP65 6000 840 COR MWS CON	11	14	17	27	18	25	31	38
96631095	JULIE 1500 LED IP65 6000 840 COR MWS E3	11	14	17	27	18	25	31	38
96630241	JULIE 1500 LED IP65 6000 840 TW	11	14	17	27	18	25	31	38
96631143	JULIE 1800 LED IP65 8000 840	7	9	11	14	7	9	11	14
96631144	JULIE 1800 LED IP65 8000 840 E3	6	8	10	13	6	8	10	13
96631300	JULIE 1800 LED IP65 8000 840 CONNECT	7	9	11	14	7	9	11	14



Lara

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96666101	LARA LED 250 800 840 WH	93	121	153	187	56	72	90	112
96666102	LARA LED 250 800 840 BLK	93	121	153	187	56	72	90	112
96666103	LARA LED 250 800 840 WH E3	93	121	153	187	56	72	90	112
96666104	LARA LED 250 800 840 BLK E3	93	121	153	187	56	72	90	112
96666109	LARA LED 250 800 840 MWS WH	93	121	153	187	56	72	90	112
96666110	LARA LED 250 800 840 MWS BLK	93	121	153	187	56	72	90	112
96666111	LARA LED 250 800 840 MWS WH E3	93	121	153	187	56	72	90	112
96666112	LARA LED 250 800 840 MWS BLK E3	93	121	153	187	56	72	90	112
96666117	LARA LED 250 800 840 PC WH	93	121	153	187	56	72	90	112
96666118	LARA LED 250 800 840 PC BLK	93	121	153	187	56	72	90	112
96628900	LARA LED 300 1000 840 BEZEL TRIM WH	93	121	153	187	56	72	90	112
96666105	LARA LED 300 1200 840 WH	93	121	153	187	56	72	90	112
96666106	LARA LED 300 1200 840 BLK	93	121	153	187	56	72	90	112
96666107	LARA LED 300 1200 840 WH E3	93	121	153	187	56	72	90	112
96666108	LARA LED 300 1200 840 BLK E3	93	121	153	187	56	72	90	112
96666113	LARA LED 300 1200 840 MWS WH	93	121	153	187	56	72	90	112
96666114	LARA LED 300 1200 840 MWS BLK	93	121	153	187	56	72	90	112
96666115	LARA LED 300 1200 840 MWS WH E3	93	121	153	187	56	72	90	112
96666116	LARA LED 300 1200 840 MWS BLK E3	93	121	153	187	56	72	90	112
96666119	LARA LED 300 1200 840 PC BLK	93	121	153	187	56	72	90	112
96666120	LARA LED 300 1200 840 PC WH	93	121	153	187	56	72	90	112
96629752	LARA LED 330 2000 840 WH	70	90	110	140	65	85	105	130
96629754	LARA LED 330 2000 840 MWS WH	70	90	110	140	65	85	105	130
96629755	LARA LED 330 2000 840 WH E3	70	90	110	140	65	85	105	130
96629756	LARA LED 330 2000 840 MWS WH E3	70	90	110	140	65	85	105	130
96629753	LARA LED 330 1800 830 WH	70	90	110	140	65	85	105	130
96630393	LARA LED 330 1800 840 BEZEL TRIM WH	70	90	110	140	65	85	105	130



Leo

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96630252	LEO LED FL IP66 75W 840 PC	26	34	42	54	13	17	21	27
96630253	LEO LED FL IP66 100W 840 PC	8	12	16	20	4	6	8	10
96630254	LEO LED FL IP66 150W 840 PC	6	8	10	12	3	4	5	6
96630255	LEO LED FL IP66 200W 840 PC	4	6	8	10	2	3	4	5
96630256	LEO LED FL IP66 210W 840 PC	4	6	8	10	2	3	4	5



Leonie

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96630335	LEONIE LED FL IP65 10W 840	147	190	234	354	73	95	117	147
96630336	LEONIE LED FL IP65 20W 840	176	228	280	352	88	114	140	176
96630337	LEONIE LED FL IP65 30W 840	116	140	186	234	58	70	93	117
96630338	LEONIE LED FL IP65 50W 840	70	90	112	140	35	45	56	70
96631096	LEONIE LED FL IP65 10W 830	147	190	234	354	73	95	117	147
96631097	LEONIE LED FL IP65 20W 830	176	228	280	352	88	114	140	176
96631098	LEONIE LED FL IP65 30W 830	116	140	186	234	58	70	93	117
96631099	LEONIE LED FL IP65 50W 830	70	90	112	140	35	45	56	70



Mike

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96644483	MIKE LED 1200 1800 830	72	94	115	144	43	56	69	87
96644484	MIKE LED 1200 1800 840	72	94	115	144	43	56	69	87
96644485	MIKE LED 600 900 830	36	47	58	72	22	28	35	43
96644486	MIKE LED 600 900 840	36	47	58	72	22	28	35	43



Monty

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
22662551	Monty Moduline LED 606 3200lm HF L830	50	65	80	100	45	60	75	90
22662560	Monty Moduline LED 606 3200lm HF L840	50	65	80	100	45	60	75	90
22170104	Monty Moduline LED 606 3200lm HF L840 E3	50	65	80	100	45	60	75	90



Zoe

SAP Code	Product Description	C10	C13	C16	C20	B10	B13	B16	B20
96666088	ZOE LED DL 110 600 840	198	257	317	396	119	155	191	239
96666089	ZOE LED DL 160 900 840	132	172	211	264	80	103	127	159
96666090	ZOE LED DL 210 1500 840	88	114	141	176	53	69	85	106
96666092	ZOE LED DL 110 600 830	198	257	317	396	119	155	191	239
96666093	ZOE LED DL 160 900 830	132	172	211	264	80	103	127	159
96666094	ZOE LED DL 210 1500 830	88	114	141	176	53	69	85	106
96666091	ZOE LED DL 210 2000 840	72	94	115	144	43	56	69	87
96666095	ZOE LED DL 210 2000 830	72	94	115	144	43	56	69	87